



Terminal B-web 93 40

Modern time and attendance

The B-web 93 40 – ideally suited for all your requirements for a time and attendance terminal. Its special feature: 'Guide by Light'. With this intuitive concept, you operate the terminal simply, conveniently and securely. The full-screen glass front has an individually illuminated capacitive keypad. It consists of five function keys (In/Out/Official Absence/Inquiry/Special Function), five special keys (for list selection or language selection) and a numeric keypad for date code or other code input. An interplay of bright and dimmed keys guides you reliably through all applications.

The time bookings of your employees are done via RFID readers – preferably LEGIC, MIFARE or HID. The memory is designed for 2,000 employees and can be adapted individually depending on the planned number of master and booking records.

The application package B-web 93 40 includes all the functions that you currently need for your time and attendance. In addition, you can use the B-web 93 40 for access control: The terminal monitors doors and communicates with access readers.

The CardLink function integrates offline door components into a security solution. These functions can be extended very easily with additional usage licenses. Intelligent service features such as 1-Click Installation or 1-Click replacement in combination with the communication software B-COMM guarantee a high system availability.

Your benefits at a glance

- meets all the requirements of modern time and attendance
- simple and intuitive operation through 'Guide by Light'
- full-screen glass front with wear-resistant keypad
- support of all conventional RFID standards
- integration of biometric identification and verification solutions
- access control functionality through the connection and control of access readers
- standard power supply via Power over Ethernet (PoE)
- Reliable and fast 1-Click installation
- innovative 1-Click analysis and 1-Click replacement in combination with B-COMM

Performance features

Hardware	B-web 93 00	B-web 93 20	B-web 93 40	B-web 93 60
Basic device with Docking station ¹	●	●	●	●
Capacitive keypad	●	●	●	●
QVGA Display 320 x 240 Punkte	●	●	●	●
User guidance Guide by Light ²	○	○	●	●
Readers				
RFID reader (LEGIC, MIFARE, HID)	●	●	●	●
Other RFID readers ⁴	○	○	○	○
Biometric module ² 500, 3.000 or 5.000 persons	○	○	○	○
Magnetic stripe reader ⁴	○	○	○	○
Interfaces				
10/100 Ethernet interface	●	●	●	●
RS-485 / RS-422 communication	○	○	○	○
Power supply				
PoE according to IEEE 802.3af	●	●	●	●
24 V AC/DC ³	○	○	○	○
230 V internal power supply unit ³	○	○	○	○
Uninterruptible power supply	○	○	○	○
Memory options				
Number of persons 200	●	●	-	-
Number of persons 1,000	○	○	-	-
Number of persons 2,000	○	○	●	-
Number of persons 10,000	○	○	○	●
Software modules				
Basic software TA1 "offline"	●	-	-	-
Basic software TA2 "offline/online"	○	●	●	●
Enhanced input list entry, numeric input, soft keys, language selection	○	○	●	●
Enhanced information display info, mailbox texts, plain text info	○	●	●	●
Option access incl. support of up to 4 subterminals	○	○	●	●
Option data encryption	○	○	○	●
Option CardLink (write LEGIC, MIFARE)	○	○	●	●
Optional AVISO programming	○	○	○	●

Remark: The effective functions available of the product depend on the system context in which it is used.

Standard ●
Option ○
Not possible -

1 Optional equipment with a circuit board in accordance with the selected power supply, interface and/or digital I/Os.

2 Determination of the version when the product is ordered. Changed design possible by replacing the terminal.

3 If changed subsequently, the docking station must be replaced.

4 Installation is done in the substructure housing when ordering and is not possible subsequently.

Any questions? We would be happy to answer any questions you may have.

dormakaba Deutschland GmbH
DORMA Platz 1
58256 Ennepetal
T: +49 2333 793-0
F: +49 2333 793-49 50
www.dormakaba.com